


Servo Transducer VGC613

for the LTI VariGrip III Controller



Rev 7/6/11

LTI Liberating Technologies, Inc.

325 Hopping Brook Road, Suite A, Holliston, MA 01746-1456 Phone 508-893-6363 FAX 508-893-9966
www.liberatingtech.com

The LTI Servo Transducer (VGC613):

This unit is designed to be used as a positional-servo transducer with the LTI VariGrip III Controller and with Otto Bock systems, allowing the user to regulate the position of the prosthetic device through body movements that pull on the transducer cord. The position of the transducer determines the position of the prosthesis. If the user pulls the transducer cord ½” (full excursion), the prosthesis fully flexes. A smaller movement of the transducer cord produces a smaller movement of the prosthesis. This motion of the prosthesis, tracking the motion of the transducer, is called “servo control”. When used to control a powered elbow for example, the transducer’s position relates directly to the position of the elbow (degree of flexion) – a fully-pulled transducer equals a fully flexed elbow. When the transducer is released, the elbow extends. Other non-servo uses of the Transducer are discussed further on. The user’s abilities and range of motion determine what body movement is best used to actuate the servo transducer.




Figure 1 - Servo Transducer




Figure 2 - Mounting Holes

Description:

The Servo Transducer consists of a linear potentiometer in a small case with an attached 8” (200mm) Bowden sheath. A Spectra™ cord (about 16” or 400 mm) exits the sheath and is supplied with a loop strap for attaching to the harness. Pulling the cord changes the resistance of the potentiometer, thus changing the speed and position of the prosthetic device. As originally set-up, the Spectra cord moves a total of ½ inch (13 mm). Depending on where you place a knot in the cord when setting up the transducer, the cord can be set to travel ½ inch or 1 inch (13 or 25 mm). The potentiometer has a small return spring which is supplemented by a secondary, adjustable spring for matching the resistance to the needs of the user.

Mounting the Transducer:

Mount the transducer on a flat surface, using the 3 flat-head #2 self-tapping screws provided (Fig 2). Alternatively, a cavity can be molded into the outer socket and the transducer can be placed between the inner and outer sockets to conceal it.

Actuation of the Transducer:

The actual location of the Transducer is less important than the location of the end of the Bowden cable. Typically, a point near the end of the sheath is fixed to a point on the posterior wing of a transhumeral socket. The other action point is the attachment of the cord running through the Bowden

sheath, often on the contralateral side of the posterior harness. Forward motion of one or both shoulders (protraction) takes the slack out of the cord and then moves the transducer mechanism.

Adjusting Length of Travel:

The unit is shipped with the Spectra cord secured to the Delrin piece as shown in Figure 3. This is the 0-½ inch travel setup. Generally this is the preferred configuration. If the user requires more travel, you can change to the 0-1 inch travel setup by removing the cover and rerouting the Spectra cord. Drill a 0.05“ diameter hole (#55 drill) through the case where shown in Figure 4. A dimple has been provided to center the drill. Cut off the knot at the black “pulley block”, and straighten the cord. Now loop the cord through the hole in the Delrin block – passing it in one hole and back out the second hole (180°), then out through the new hole in the case. Tie a “figure 8” knot just outside the case. The Spectra™ cord is slippery (ultra high-molecular-weight polyethylene), so you should trap a little “superglue” (cyano acrylic cement) in the interior of any permanent knot or it will work loose. Have your user try both travel set-ups before gluing any knots.




Figure 3 - Single Spectra Cord - ½” Travel



Figure 4 – Drill Hole for Rerouting Spectra Cord - 1” Travel

Spring Return Adjustment:

Usually the transducer is pulled by shoulder motion or by chest expansion. The muscles that initiate these motions are relatively strong and you may need a strong spring for your user to develop the best possible “feel” for where the transducer is in its travel. The spring tension provides feedback to the user. An adjustment screw (Figure 5) is located on the end of the transducer case. Rotating this screw **counter-clockwise**, will **reduce** tension in the spring. Rotating it **clockwise** will **increase** spring tension, assisting the user in feeling when the transducer engages. Most users will need little or no pretension, but will need at least the weakest spring to overcome friction in the system.




Figure 5 - Spring Tension Adjustment



Figure 6 – Securing the End of the Bowden Cable

The case cover secures the Bowden cable sheath as shown in Figure 6. Once the sheath is in place, tighten the two cover screws, then make sure that the set screw on the top of the case is tight against the Bowden cable. If the sheath is too long, it can be cut to length. Remove the Spectra cord and cut both the Bowden shroud and the inner Teflon liner to the desired length. Then re-thread the Spectra cord through the Bowden cable and attach the end piece.

Routing the Spectra Cord:

The Transducer is supplied with the Bowden sheath attached. The other end of the sheath will be at the socket-side anchor point. For the transhumeral amputee using protraction of the shoulder, this anchor is usually placed right over the abduction axis of rotation on the posterior wing of the socket. The goal for the user is to be able to abduct and forward flex with minimal pull on the cord while maximizing the motion that results when the shoulder is protracted.

Connecting to the LTI VariGrip Controller:




Figure 7 - Servo Transducer connection to VariGrip Controller

When the LTI Servo Transducer is used with a LTI VariGrip Controller, the cable is plugged into the 6-conductor input connector on the top of the controller (as shown to the left – Fig 7).



Figure 8 – 6-conductor connector